

OPEN

Compute Project

Design Guide for Open Rack Management Backplane Connection

Draft: November 7th, 2016

Version: 1.0

Authors:

Ethan Long, Intel

John He, Intel

Terry Trausch, Intel

Alex Lee, Quanta

Alan Chang, Quanta

1 Contents

| | | |
|-----|---|----|
| 1 | Contents | 2 |
| 2 | Revision History | 3 |
| 3 | Introduction | 4 |
| 3.1 | Goal | 4 |
| 3.2 | Confidentiality | 4 |
| 3.3 | Terms and Acronyms | 4 |
| 4 | Overview | 5 |
| 4.1 | MBP Connection in the Rack | 5 |
| 4.2 | MBP Connection on IT Equipment | 6 |
| 4.3 | MBP Mechanical Requirements | 7 |
| 5 | Rack MBP Connector | 8 |
| 5.1 | Connector Part Numbers | 8 |
| 5.2 | Connector Pin Out | 9 |
| 6 | Management Backplane Location in Open Rack | 13 |
| 7 | Appendices | 16 |
| 7.1 | Open Compute Mechanical Reference Documents | 16 |
| 7.2 | Design Collateral | 16 |
| 7.3 | Other Reference Materials | 16 |

2 Revision History

| Revision | Date | Changes |
|-------------|------------|--|
| 0.1 | 07/31/2015 | First Draft |
| 0.2 | 8/7/2015 | Second Draft |
| 0.3 | 8/11/2015 | 3 rd Draft |
| 0.4 | 8/12/2015 | 4 th Draft |
| 0.5 | 8/18/2015 | Added drawing images to Figures 6, 7, and 8. |
| 0.52 | 9/30/2015 | Updated descriptions in pin out table |
| 0.6 | 2/17/2016 | Added clarifying information on connector misalignment, alternate connector vendor, connection sequencing; Updated pin names |
| 1.0 | 11/7/2016 | Updated figures 7 and 8 with tolerances for key dimensions; updated references to proposed Open Rack 2.0 spec |

3 Introduction

3.1 Goal

This document describes a mechanical implementation of a rack management backplane connection (MBP) in an Open Rack. IT equipment equipped with the appropriate connector could then mate to the rack MBP via a blind mate installation into the rack. This will supplement the proposed Open Rack Standard v. 2.0 which does not address the use of a management backplane.

The benefits of a rack MBP include:

- Less cabling at the front of the rack, which also potentially reduces service costs
- Reduced network port count
- A physically isolated rack management network

3.2 Confidentiality

The rights and confidentiality of this document will be controlled by Open Compute Project.

3.3 Terms and Acronyms

| Acronym | Description |
|------------------|--|
| MBP | Rack Management Backplane |
| Bus bar | A pair of main copper strips which provide 12V DC power for all components in rack |
| OCP Rack: | Same as Open Rack |
| OU Height | Open Compute Rack Unit Height, 1 OU Height = 48mm |
| Sled | IT equipment tray |

4 Overview

4.1 MBP Connection in the Rack

Intel and Quanta recently collaborated on the development of a rack MBP for Open Compute. Intel has showcased hardware featuring this design in a demo rack shown at Intel Developer Forum 2015 and at OCP Summit 2015 and 2016.




Figure 1 A demo rack shown at IDF 2015, the result of a joint effort between Intel and Quanta

The Open Rack Standard v 2.0 allows for use of a single central bus bar pair for distributing rack power, or for use of all three bus bar locations outlined in previous versions of the standard. Intel and Quanta chose to reduce the number of bus bars used, so that one of the side bus bar locations might be used for the rack management hardware. Figure 2 features a front view of a rack with a MBP located at the left hand bus bar location, with a central bus bar remaining for the delivery of rack power. The MBP does not exceed the width of the allocated bus bar zone at that location.

Figure 2 also defines the key mechanical interfaces of the backplane: The backplane connector and alignment holes. The backplane connector is suitable for blind-mate applications and can tolerate up to 2 mm of X-Y (horizontal/vertical) misalignment. The alignment holes in the backplane module are intended to provide a means for coarse adjustment of the system-to-rack misalignment by accepting alignment pins from the installed IT equipment. By using the coarse alignment pins, the system may allow additional misalignment beyond what the backplane connector can resolve.




Figure 2 Front view of the Open Rack featuring a management backplane (MBP), in place of the left-hand bus bar.

4.2 MBP Connection on IT Equipment

The critical mechanical interfaces on compatible IT equipment include the MBP header and the coarse alignment pins (shown in Figure 3). It is recommended that the MBP interface at the rear of the IT equipment chassis incorporate a floating or compliant mounting to accommodate the significant chassis and rack tolerances without inhibiting mating to the backplane or imparting side loads onto the connectors.

For example, the Quanta/Intel implementation used an 8.2 mm diameter tapered alignment pin and a compliant mounting on the IT equipment. This design can resolve connector misalignment up to ± 4 mm in both the X and Y (horizontal and vertical) directions.




Figure 3 Example of a MBP interface on a 20U server chassis, including a single MBP header mounted to an interposer card, and coarse alignment pins.

4.3 MBP Mechanical Requirements

The architecture and hardware of a rack MBP may vary depending on the application, but there are some key features that must remain consistent in order to ensure compatibility with properly equipped IT equipment of any integer “OU” height. (IT equipment 1/2 OU in height is not supported by this design.) This document will specify the following:

- A common connector for use in the MBP application
- A common pin out scheme for all MBP connectors
- Location of connector and alignment features in the Open Rack

5 Rack MBP Connector

5.1 Connector Part Numbers

The connectors chosen for the MBP interface are FCI PWR LoPro series headers and receptacles, with 2 power blades and 25 signal pins (see Figure 4):

IT Equipment-side Header: **FCI 10122460 - 011LF**

Rack-side Receptacle: **FCI 10121382-R02253SLF**




Figure 4 The Rack MBP connectors: IT Equipment MBP header (left), and rack MBP receptacle (right)

TE Connectivity also offers the following connector part numbers, which match the FCI spec:

Header: **8-1926730-1**

Receptacle: **1-1892782-2**

5.2 Connector Pin Out

The pin assignments for the connections are shown in Figure 5.




Figure 5 Signal pin number assignments shown on a front view of the MBP Header

The connections in the MBP connector pair are sequenced to provide three stages of pin engagement. The power pins engage first, followed by most signal pins. There are two short signal pins (A2/E2) that engage last. The backplane connector is also positioned in the rack such that, when compatible IT equipment is installed, the bus bar power connection is made before the management backplane connection is established.

Table 1, below, specifies the tray I/O to the MBP over the FCI MBP connectors. Inputs (including the label RX) are defined as inputs to the tray from the MBP and outputs (including the label TX) as outputs from the tray to the MBP.

Table 1 Tray Management Backplane Connector I/O

| Name | Pin | Voltage | Type | Description |
|--|----------------|---------|------|---|
| TRAY_INT1_N | C4 | 3.3V | O | Tray Interrupt 1: Interrupt signal from the tray management subsystem to the MBP, active low. |
| TRAY_ID[2] TRAY_ID[1] TRAY_ID[0] | B2 C2 D2 | 3.3V | I | Tray ID: Signals from the management backplane to the tray indicating the location of the tray within the rack's management backplane segment. The largest MPB segment is limited to eight tray interfaces (one binary ID setting per OU). |
| POWER_CRIT_N | B5 | 3.3V | I | Throttle, Power to the Tray Critical: This signal indicates that the DC power supplied to the tray is in a critical state. The expected action for the tray is to quickly reduce power consumption by reducing IT equipment power consumption. The tray DC power is in a critical state when this signal is logic 0. |
| TRAY_RESET_N | C5 | 3.3V | I | Tray, Management CPU Reset: Signal indicating the tray management controller(s) should reset. This signal has two definitions. If management controllers see this signal active for less than four seconds, they should initiate a graceful reset. If management controllers are unable to provide a graceful/warm reset, this signal may be held for four seconds or more resulting in a forced/cold reset. This is intended to be the equivalent function of a reset button to the management controller. The reset is active when this signal is logic 0. |
| BP_PRSENT_N | A2 | 3.3V | I | Backplane Present: This signal indicates to the tray management controller that the tray is physically connected to a management backplane. The management backplane is present when this signal is logic 0. A2 is one of two short signal pins that are the last to establish a connection when installing a tray in a rack. |
| TRAY_PRSENT_N | A4 | 3.3V | O | Tray Present: Signal indicating to the MBP that a tray is physically connected to that MBP interface. A tray is present when this signal is logic 0. |
| KX_TX_P, KX_TX_N | B1 A1 | -- | O | Management Ethernet KX TX: One high speed serial differential output pair complying with the IEEE Ethernet 1000Base-KX specification. This provides a tray management network interface. |

| Name | Pin | Voltage | Type | Description |
|-----------------------|----------|---------|------------|--|
| KX_RX_P, KX_RX_N | E1 D1 | -- | I | Management Ethernet KX RX: One high speed serial differential input pair complying with the IEEE Ethernet 1000Base-KX specification. This provides a tray management network interface. |
| TRAY_INT2_N | C3 | 3.3V | O | Tray Interrupt 2: Interrupt generated to the MBP when vital status of any tray module changes. The interrupt is asserted when this signal is logic 0. |
| IPMB_CLK, IPMB_DAT | E3 D3 | 3.3V | I/O I/O | IPMB Clock, Data: An I2C bus supporting the IPMB protocol for management traffic destined to the tray that handles traffic between the management backplane (initiator) and the tray management controller (target). |
| UART_TX | D5 | 3.3V | O | UART 1 TX: A TTL level serial output from any module in the tray or from the tray management controller to the MBP. The default baud rate is 115K at 8 bits, no parity, and one stop bit. Recommend for trays that include a front panel and MBP interface for management console that this signal be a simple buffer copy of the UART TX to each location instead of using a multiplexer that enables and disables the interface to each location. |
| UART_RX | E5 | 3.3V | I | UART 1 RX: A TTL level serial input from the MBP to any module in the tray or to the tray management controller. The default baud rate is 115K at 8 bits, no parity, one stop bit. Recommend for trays that include a front panel and MBP interface for management console that this signal be a simple wire-or of signal from the front panel and the MBP to the management controller instead of using a multiplexer that enables and disables the interface to each location. |
| TRAY_MBP_CTRL_EN_N | D4 | 3.3V | I | Tray MBP Controller Power Enable: A TTL level input signal that may control the power state of the tray management controller. This is intended to be the equivalent function of a power button to the management controller. The power is enabled when this signal is logic 0. Note: The signal does NOT necessarily control the power flow between the rack bus bar and the rest of the tray electronics. It is ONLY required to control of power to the tray management controller. |

| Name | Pin | Voltage | Type | Description |
|------------|--|---------|------|--|
| NC | A3 A5 B3 B4 | -- | -- | No Connect: Reserved. |
| 12V | P_A2 P_B2 P_C2 P_D2 P_E2 P_F2 | 12V | P | <p>12V Output Power: This is power sourced from the tray to the management backplane exclusively for use by active devices that may exist on the management backplane. It may be used as a power source for fans. Recommend that this power be sourced through a diode so that one tray does not have current flow to another tray.</p> <p>The current limit is 22 Amps.</p> <p>This is power sourced from the tray (that connects to a power bus bar) to the management backplane. It is strongly recommended that this output power be diode isolated from the rest of the tray power so that one tray does not have a power path to another tray.</p> |
| GND | C1 E2 E4 P_A1 P_B1 P_C1 P_D1 P_E1 P_F1 | -- | GND | <p>GND: Ground.</p> <p>The current limit is 22 Amps.</p> <p>E2 is one of two short signal pins that are the last to establish a connection when installing a tray in a rack.</p> |

6 Management Backplane Location in Open Rack

The rack MBP shall occupy the left-most bus bar location, and provide connections for IT equipment at 10U increments. Figures 6, 7, and 8 define the location of key connector and alignment features with respect to existing Open Rack features.



Figure 6 Side View of MBP Connection in the Open Rack




Figure 7 Front and Top Views of MBP Connection Features and Locations in the Open Rack




Figure 8 Front Detail View of MBP Connection

7 Appendices

7.1 Open Compute Mechanical Reference Documents

The following specifications are available on the Open Compute website:

- Open Rack Standard Preliminary v 2.0
(<http://files.opencompute.org/oc/public.php?service=files&t=38654e3d547eac87e1607cf7bd4f97b0>)
- Open Rack Design Guide v 1.1
(<http://files.opencompute.org/oc/public.php?service=files&t=2db91c3317610dfcc383ba4dc720a186>)

7.2 Design Collateral

3D CAD geometry for the Quanta rack implementation of MBP connection is available for community reference.

7.3 Other Reference Materials

- I2C Specification –
(http://www.nxp.com/documents/user_manual/UM10204.pdf)
- IEEE 802.3 Specification -
(<http://standards.ieee.org/about/get/802/802.3.html>)